

	LECTRONI EVICES LTI ALVERN - ENGLAND	C D. G/	AS DETECTOR TY	PE ED 811	Ø	
Certificate numbe Baseefa03ATEX0 BAS21UKEX0600	rs: 507 Um:253∨ ¶	SENSOR 1 A2 A1 FAULT POWER RESET	SENSOR 2 A2 A1 FAULT LOW VOLTAGE	SENSOR 3 A2 A1 FAULT	SENSOR 4 A2 A1 FAULT ALARM TEST	
Serial No	Input Voltage:	VAC				

ED811 GAS DETECTOR

INSTRUCTION MANUAL

Address: Enigma House, Enigma Business Park, Malvern, Worcestershire, WR14 1GD Tel: +44 (0)1684 891500 Fax: +44 (0)1684 891600 Email: sales@electronic-devices.co.uk Website: www.electronic-devices.co.uk

INDEX

	PAGE
IMPORTANT NOTES	2
ATEX ESSENTIAL SAFETY REQS	2
MARKING	4
GENERAL	4
INSTALLATION	4
CONTROL UNIT	4
SENSOR WIRING	5
SENSORS	6
SITTING	6
UNUSED SENSOR POSITIONS	6
OPERATING INSTRUCTIONS	6
ENGINNERS OVERRIDE	6
CALIBRATION	7
SEMICONDUCTOR SENSORS	7
EDS/C & EDS/P SENSORS	7
CONFORMITY & CERTIFICATES	9
DECLARATION OF CONFORMITY	9
ED811 Ex-TYPE EXAMINATION CERTIFICATE	12
ZB EX-TYPE EXAMINATION CERTIFICATE	18

IMPORTANT NOTES

1. THE EQUIPMENT MUST NOT BE MODIFIED IN ANY WAY SINCE MODIFICATIONS WILL INVALIDATE INTRINSIC SAFETY CERTIFICATION.

2. DANGEROUS VOLTAGES ARE PRESENT WITHIN THIS 240V CONTROL UNIT AND CARE SHOULD TAKEN DURING SERVICING AS HIGH VOLTAGES ARE PRESENT ON THE BASE, PRINTED CIRCUIT BOARD AND MAY BE PRESENT ON OUTPUT CONTACTS.

3. IT IS IMPORTANT TO NOTE THAT THE ED811 CONTAINS ZENER BARRIERS, TYPE ZB1, WHICH ARE "POTTED" IN EPOXY RESIN. THE ZENER BARRIERS CONTAIN FUSES, WHICH ONCE DAMAGED ARE NOT REPLACEABLE. THE FUSES INSIDE THE ZENER BARRIER WILL BLOW IF EVEN TEMPORARY SHORT CIRCUITS ARE PLACED ON THE SENSOR WIRING THUS RENDERING THE ZENER BARRIER INOPERABLE AND ARE NOT REPAIRABLE. GREAT CARE SHOULD THEREFORE BE TAKEN TO AVOID INADVERTENT SHORT CIRCUITS.

4. ELECTRONIC DEVICES STRONGLY RECOMMEND CONSULTATION OF THE HSE PUBLICATION EH40, WHICH LISTS THE PERMITTED LEVELS OF EXPOSURE TO MOST TOXIC GASES.

ATEX ESSENTIAL SAFETY REQUIREMENTS

The ED811 Gas Detectors internally mounted Zener Barriers and associated gas sensors are ATEX / UKCA certified Intrinsically Safe and the important requirements listed below need to be followed.

1. The equipment must only be installed, operated and maintained by trained competent personnel.

2. This apparatus has been designed in accordance with EN60079-0:2018 and EN60079-11:2012 which are harmonised. Therefore the apparatus has been designed to meet the fault tolerant requirements of Associate Apparatus for Category 'ia'.

3. The installation and maintenance must be in accordance with all appropriate international, national and local standard codes of practice and site regulations for intrinsically safe apparatus.

4. The installation and maintenance must be in accordance with the instructions contained in this installation and maintenance manual.

5. Access to the circuitry must not be made during operation.

6. This product is an associated electrical apparatus and must not be installed in the hazardous area without the provision of further certified hazardous area protection.

7. The product must not be subjected to mechanical and thermal stresses in excess of those permitted in the certification documentation and the instruction manual. If necessary the product must be protected by an enclosure to prevent mechanical damage.

8. The product must not be installed in a position where it may be attacked by aggressive substances.

9. The product must be protected from excessive dust by an enclosure etc.

10. The product can not be repaired by the user and must be replaced by an equivalent certified product. Repairs should only be carried out by the manufacturer or approved service centre.

MARKING

All units have a rating label which carries the following important information:-

Model type:	GAS DETECTOR TYPE ED811		
Input voltage:	110VAC/220VAC/240VAC (delete as appropriate)		
Vmax in; Um:	Um: 250V		
Code: Certificate no:	[Ex ia Ga] II C CE Baseefa03ATEX0507 UK BAS21UKEX0600		
Epsilon x, gas group and category:	(Ex) II (1) G		
CE marking,	CE 0598	UK marking	UK
Notified body number:		Notified body number:	CA 1180
Serial no:	() - serial number must be er	ntered here
Year of construction:) - year of manufacture mus	st be entered here

GENERAL

The ED811 is a fixed installation gas detection system, which can detect a wide range of flammable and toxic gases dependent upon sensor type used.

The ED811 is designed for mains input voltage and it is important to ensure the input voltage of the control unit is the same as the supply available. Special consideration should be given to the "Hazardous Area common connection" terminal. This should normally be connected to a good quality earth suitable for intrinsically safe equipment.

Attention is drawn to the need for correct cabling, particularly to the sensors located in the Hazardous Area. The cable supplied by ED for use with the ED811 has been tested to ensure correct parameters, see installation section of this manual.

Attention is also drawn to the need for calibration soon after installation. When supplied alarm levels are approximately set for the target gas (if stated with order) so that a measure of immediate protection is obtained once correct operation has been ensured.

INSTALLATION

Note only ED manufactured sensors, which are certified Intrinsically Safe, can be connected to the ED811 and fitted in the Hazardous Area. The ED811 control unit and all uncertified equipment should be located in the Safe Area only.

CONTROL UNIT

The unit should be mounted in a convenient position for the operator away from possible mechanical damage or ingress of moisture and allowing the clear-hinged lid to swing open for ease of calibration etc.

The enclosure is fixed to a bulkhead with screws through one keyhole and two fixed holes in the base. To obtain access to the two lower slotted holes remove the terminal cover. Note it is not usually necessary to remove the front panel and PCB assembly during installation or calibration.

Only the relay contacts marked NON ALARM ACCEPT should be used for control functions as they will remain in the alarm state until the gas has cleared and the unit reset. Sensor cable entry must only be made through the intended hole via either the

standard rubber grommet or cable gland.

Sensor cables must not cross or lie over each other or safe area cables see *Fig 1*.

In addition to the zener barrier fuses (which cannot be replaced) each sensor is individually fused on the base board PCB.

If a sensor fails to respond the nominal 5V between blue and brown terminals should be checked and the 160mA quick blow (F) changed if necessary.

SENSOR WIRING

The Sensor cable should meet the following specification as listed in the Zener Barrier (ZB1) certificate, see page 15.

The total capacitance of the cable must not exceed 6.8uF for EDS/C and EDS/P or 8.8uF for the EDF sensor. Also the inductance or inductance to resistance (L/R) ratio should not exceed 0.06mH or $14uH/\Omega$ respectively.



FIG 1



SAFE AREA WIRING

HAZARDOUS AREA WIRING

FIG 2



Relay contact rating: 2A at 240VAC Non Inductive

FIG 3

SENSORS

SENSORS

Type EDF 1B, 2B, 3B and 3Bfig are semiconductor elements housed in a certified flameproof stainless steel housing. The housing has a male M32 thread which can be screwed into a conduit or suitable junction box. The semiconductor sensors are available in the following types:-

a) EDF1B flameproof. Suitable for the detection of flammable gases such as Ammonia, Butane, Propane and some toxic gases, for more gases see list available.

b) EDF2B flameproof. Suitable for the detection of flammable gases such as Methane, Hydrogen and some toxic gases, for more gases see list available.

c) EDF3B fig flameproof. Suitable for the detection of most Freons such as R11, R12, R22, R143A, R134A etc.

The EDS/C IS Transmitter is a intrinsically safe junction box complete with head electronics and electrochemical cell gas sensor suitable for the detection of various toxic gases. Many different electrochemical cells are available and EDL should be consulted to advise on correct sensor type.

The EDS/P IS Transmitter is a intrinsically safe junction box complete with head electronics and catalytic (pellistor) gas sensor suitable for the detection of flammable gases. Contact EDL for advice on correct sensor type.

SITING

The sensor heads should be placed lower than gas appliances when the gas to be detected is heavier than air. If the gas is lighter than air then the sensors should be placed above possible sources of leaks. Consideration should be given to the temperature of the gas at the time during a leak, for example if a serious Ammonia leak occurs in a refrigeration plant it can leak as a liquid and stay at floor level for some time even though Ammonia is lighter than air. In this instance sensors at low and high levels are normally fitted.

Attention should be given to the probable gas flow in each particular installation to site the sensors in the most advantagous position. In living quarters particular consideration should be given to carbon monoxide, it is advisable that some of the sensors are mounted at head height.

The sensors are sealed into their stainless steel enclosures and no attempt should be made to open them on site, if necessary they should be returned to EDL for repair/servicing.

UNUSED SENSOR POSITIONS

When all of the sensor positions are not being used the spare position should have the dip switches on the control PCB set to "standard sensors" and a terminating resistor of $47K\Omega$ fitted to avoid the fault lights and relay operating. This is normally done before the unit leaves the factory as standard.

SETUP AND CALIBRATION

When power is first applied the power light should illuminate immediately. The A1 and A2 lights of semiconductor sensors will illuminate within a few seconds and will be ready to be reset after a few minutes, provided the sensors are in clean air. The alarm lights and relays latch and the reset switch must be pressed to clear any alarms.

The output functions can be easily tested by pressing the "alarm test" button. If the "alarm accept" button is pressed any sounders or beacons connected will be muted.

When the input supply drops so low as the control unit cannot function correctly the low voltage light will illuminate and the fault relay will activate.

ENGINEERS OVERRIDE

Should be used with caution as all ALARMS are disabled for a period of approximately 30minutes. A hidden switch is located to the left of the reset switch. Pressed through the front panel using a small screwdriver all Alarms are Isolated and the Fault Buzzer sounds. Operate the hidden switch to the right of the Reset switch (keeping it pressed for several seconds) and all Alarms will be returned to the operational state and the Fault Buzzer will silence.

CALIBRATION

Before dispatch the alarm levels are approximately set for the target gas (if stated with order) or set to 25% and 50% LEL butane so that a measure of immediate protection is obtained once correct operation has been ensured.

Once the sensors and control unit have been in operation for a minimum of 24 hours calibration can be attempted. Calibration should be repeated at least every twelve months with regular checks in between.

Calibration must take place in a clean air condition to ensure accuracy.

SEMICONDUCTOR SENSORS

1. Immerse the sensor in the correct concentration for the A1 alarm, if using a continuous flow do not use a flow rate of above 0.3L/min.

2. After allowing the sensor time to settle (10-20 seconds) adjust the appropriate potentiometer located under the A1 light, accessed through the front panel. Rotating clockwise increases sensitivity until the A1 light just illuminates, if the light omes on prematurely wind anticlockwise whilst continuously pressing the reset switch until the light goes out and then clockwise until it just illuminates.

3. Immerse the sensor in the correct concentration for the A2 alarm, if using a continuous flow do not use a flow rate of above 0.3L/min.

4. After allowing the sensor time to settle (10-20 seconds) adjust the appropriate potentiometer located under the A2 light, accessed through the front panel. Rotating clockwise increases sensitivity until the A2 light just illuminates, if the light comes on prematurely wind anticlockwise whilst continuously pressing the reset switch until the light goes out and then clockwise until it just illuminates.

5. Repeat steps 1-4 for all semiconductor sensors fitted.



EDS/C AND EDS/P TRANSMITTERS INITIAL SETUP

It is vitally important that the ED811 and EDS/C or P transmitter are calibrated together ensuring that the ED811 indicates an alarm at the correct concentration. After installation is complete the following setup procedure should be followed matching the EDS/C or P, ED811 and cable run together.

EDS/C SENSORS

1. At EDS/C transmitter measure between – I/P and + I/P, ensure voltage reading is in the range 4.75 – 5.4V with a digital volt meter.

2. Using the correct calibration gas for your low alarm, ensure the calibration of the EDSC Transmitter using the EDSC calibration instructions. Whilst the EDSC is giving the correct output go to the ED811 control unit and adjust the A1 (located under the A1 light, accessed through the front panel) potentiometer until the A1 light just illuminates. Rotating clockwise increases sensitivity until the A1 light just illuminates, if the light comes on prematurely wind anticlockwise whilst continuously pressing the reset switch until the light goes out and then clockwise until it just illuminates.

3. Using the correct calibration gas for your high alarm, ensure the calibration of the EDSC Transmitter using the EDSC calibration instructions. Whilst the EDSC is giving the correct output go to the ED811 control unit and adjust the A2 (located under the A2 light, accessed through the front panel) potentiometer until the A2 light just illuminates. Rotating clockwise increases sensitivity until the A2 light just illuminates, if the light comes on prematurely wind anticlockwise whilst continuously pressing the reset switch until the light goes out and then clockwise until it just illuminates.

Example of calculating expected output voltage

The output of the EDSC* ranges from 0.1 to 0.5V (zero to full scale). If Full scale is 1000ppm NH3 then:

250ppm output : (0.4 x 0.25 + 0.1)	=	0.2V
500ppm output: (0.4 x 0.5 + 0.1)	=	0.3V
1000ppm output: (0.4 x 1 + 0.1)	=	0.5V

EDS/P SENSORS

1. At EDS/P transmitter measure between – I/P and + I/P, ensure voltage reading is in the range 4.0 -5.4V with a Digital volt meter.

2. Using the Zero adjustment potentiometer on the EDS/P, rotate clockwise until the 25% lamp is just illuminated or 0.2V is measured on the O/P terminal w.r.t 0V.

3. Go to the ED811 Control unit and adjust the A1 potentiometer (located below the A1 light and accessed through the front panel) until the A1 light just illuminates. Rotating clockwise increases sensitivity until the A1 light just illuminates, if the light comes on prematurely wind anticlockwise whilst continuously pressing the reset switch until the light goes out and then clockwise until it just illuminates.

4. Back at the EDS/P again using the Zero adjustment potentiometer on the EDS/P, rotate clockwise until the 50% lamp is just illuminated or 0.3V is measured on the O/P terminal w.r.t 0V.

5. Go to the ED811 Control unit and adjust the A2 potentiometer (located below the A2 light and accessed through the front panel) until the A2 light just illuminates.

6. Using the EDS/P instructions return the output to Zero and calibrate the sensor. Remember the Sensor requires a minimum of 24 hours to settle otherwise the calibration WILL NOT be accurate.

Example of calculating expected output voltage

The output of the EDSP* ranges from 0.1 to 0.5V (0 to full scale). If Full scale is 10,000ppm NH3 then:

2,500ppm output: (0.4 x 0.25) + 0.1	=	0.2V
5,000ppm output: (0.4 x 0.5) + 0.1	=	0.3V
10,000ppm output: (0.4 x 1) + 0.1	=	0.5V

* The output range stated is correct when the EDSC / EDSP is connected to the ED811, if tested separately the output range will be 0.2 to 1.0VDC.



EU/UK Declaration of Conformity

Manufacturer:	Electronic Devices I	Ltd		
Address:	Enigma House Enigma Business Park Malvern Worcestershire WR14 10	GD		
Product:	GAS DETECTOR TYPE	PE ED81*	k	
Model Type:	ED810, ED811			
Notified /Approved Bodies:	SGS Fimko Oy Takomotie FI-00380 Helsinki Finland	0598	SGS Baseefa Ltd Rockhead Business park Standen Lane Buxton, SK17 9RZ	1180
Certificate No.:	ATEX Baseefa03AT UKCA BAS21UKE	FEX0507 X0600		
Marking:	Group II Category(1)G	[Ex ia Ga	a] IIC	

We hereby declare in our sole responsibility that the product, which is the subject of this declaration, is in conformity with the following standards or normative documents:

Following the provisions of:	
Directive:	
Regulations / Statu	itory Instruments:

2014/34/EU SI 2016, UKSI 2016: 1107

Harmonised / Designated Standards Used: EN 60079-0: 2018

EN 60079-11: 2012

Other Standards and Specifications:

This product has been manufactured, finally inspected and tested under a quality system, which the notified body has approved.

Date: 20 January 2025 *Place of Issue:* Malvern

G. Roberthal

Geoff Southall, C.Eng. MIEE. MRIN Company Owner

Gas Detector Type ED81* - Jan 2025 (Revision 13)



EU/UK Declaration of Conformity

Manufacturer: Address:	Electronic Devices Ltd Enigma House Enigma Business Park Malvern Worcestershire WR14 1GD	
Product:	SHUNT ZENER DIODE SA	FETY BARRIER TYPE ZB*
Model Type:	ZB1, ZB2, ZB3, ZB4, ZB5, Z	B6
Notified / Approved Bodies:	SGS Fimko Oy 0598 Takomotie FI-00380 Helsinki Finland	SGS Baseefa Ltd1180Rockhead Business parkStanden LaneBuxton, SK17 9RZ
Certificate No.:	ATAX BAS99ATEX714 UKCA BAS21UKEX059	9U 9U
Marking:	Group II Category(1)G [Ex ia Ga] IIC (-20°C≤Ta ≤+60°C)	

We hereby declare in our sole responsibility that the product, which is the subject of this declaration, is in conformity with the following standards or normative documents:

Following the provisions of : Directive: Regulations / Statutory Instruments:

2014/34/EU SI 2016, UKSI 2016: 1107

Harmonised / Designated Standards Used: EN IEC 60079-0: 2018

EN 60079-11: 2012

Other Standards and Specifications:

This product has been manufactured, finally inspected and tested under a quality system, which the notified body has approved.

Date: 20 January 2025 *Place of Issue:* Malvern

G. aborted

Geoff Southall, C.Eng. MIEE. MRIN Company Owner

Shunt Zener Diode Safety Barrier Type ZB* - Jan 2025 (Revision 13)



EU/UK Declaration of Conformity

Manufacturer:Electronic Devices LtdAddress:Enigma HouseEnigma Business ParkMalvernWorcestershire WR14 1GD				
Product:	SHUNT ZENER DIO	DE SAFE	TY BARRIER TYPE ZB	*
Model Type:	ZB8			
Notified / Approved Bodies:	SGS Fimko Oy Takomotie FI-00380 Helsinki Finland	0598	SGS Baseefa Ltd Rockhead Business park Standen Lane Buxton, SK17 9RZ	1180
Certificate No.:	ATEX BAS99ATE UKCA BAS21UKE	X7149U X0599U		
Marking:	Group II Category(1)G [Ex ia Ga] IIB (-20°C≤Ta ≤ +60°C)			

We hereby declare in our sole responsibility that the product, which is the subject of this declaration, is in conformity with the following standards or normative documents:

Following the provisions of : Directives: Regulations / Statutory Instruments:

2014/34/EU SI 2016, UKSI 2016: 1107

Harmonised / Designated Standards Used: EN IEC 60079-0: 2018

EN 60079-11: 2012

Other Standards and Specifications:

This product has been manufactured, finally inspected and tested under a quality system, which the notified body has approved.

Date: 20 January 2025 *Place of Issue:* Malvern

G. abortal

Geoff Southall, C.Eng. MIEE. MRIN Company Owner

Shunt Zener Diode Safety Barrier Type ZB8 - Jan 2025 (Revision 13)



1 EU - TYPE EXAMINATION CERTIFICATE

Equipment or Protective System Intended for use in Potentially Explosive Atmospheres Directive 2014/34/EU

3 EU - Type Examination Certificate Baseefa03ATEX0507 – Issue 3 Number:

- **3.1** In accordance with Article 41 of Directive 2014/34/EU, EC-Type Examination Certificates referring to 94/9/EC that were in existence prior to the date of application of 2014/34/EU (20 April 2016) may be referenced as if they were issued in accordance with Directive 2014/34/EU. Supplementary Certificates to such EC-Type Examination Certificates, and new issues of such certificates, may continue to bear the original certificate number issued prior to 20 April 2016.
- 4 Product: Gas Detector Type ED81*
- 5 Manufacturer: Electronic Devices Ltd
- 6 Address: Malvern, Worcestershire, WR14 1GD
- 7 This re-issued certificate extends EC Type Examination Certificate No. Baseefa03ATEX0507 to apply to product designed and constructed in accordance with the specification set out in the Schedule of the said certificate but having any variations specified in the Schedule attached to this certificate and the documents therein referred to.
- 8 SGS Finko Oy, Notified Body number 0598, in accordance with Article 17 of Directive 2014/34/EU of the European Parliament and of the Council, dated 26 February 2014, certifies that this product has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of products intended for use in potentially explosive atmospheres given in Annex II to the Directive.
- **8.1** The original certificate was issued by SGS Baseefa Ltd (UK Notified Body 1180). It, and any supplements previously issued by SGS Baseefa Ltd have been transferred to the supervision of SGS Fimko Oy (EU Notified Body 0598). The original certificate number is retained.

The examination and test results are recorded in confidential Report No. See Certificate History

9 Compliance with the Essential Health and Safety Requirements has been assured by compliance with:

EN IEC 60079-0:2018 EN 60079-11:2012

except in respect of those requirements listed at item 18 of the Schedule.

- 10 If the sign "X" is placed after the certificate number, it indicates that the product is subject to the Specific Conditions of Use specified in the schedule to this certificate.
- 11 This EU TYPE EXAMINATION CERTIFICATE relates only to the design and construction of the specified product. Further requirements of the Directive apply to the manufacturing process and supply of this product. These are not covered by this certificate.
- 12 The marking of the product shall include the following:

B II (1)G [Ex ia Ga] IIC (-20°C \leq Ta \leq +60°C)

SGS Fimko Oy Customer Reference No. 0344

Project File No. 20/0453

This document is issued by the Company subject to their General Conditions for Certification Services accessible at http://www.sgs.com/en/Terms-and-Conditions.aspx. Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained herein reflects the Company's findings at the time of their intervention only and within the limits of Client's instructions, if any. It does not necessarily indicate that the equipment may be used in particular industries or circumstances. The Company's sole responsibility is to its Client and this document does not exonerate parties to a transaction from exercising all their rights and obligations under the transaction documents. This document cannot be reproduced except in full, schedule included, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.

SGS Fimko Oy

Särkiniementie 3 P.O. Box 30 FI-00211 Helsinki Finland Telephone +358 (0)9 696 361 Fax. +358 (0)9 692 5474 e-mail <u>sgs.fimko@sgs.com</u> web site <u>www.sgs.fi</u> Business ID 0978538-5

Tuomas Hänninen SGS Fimko Oy

BAS-CERT-081

ED811 - GAS DETECTOR

ED811 IM REV 8 - 11.02.2025

12

Issue 1



Schedule

13

14

Certificate Number Baseefa03ATEX0507 – Issue 3

15 Description of Product

A Gas Detector Type ED81* is a control unit designed to power and monitor up to 4 remote gas sensors (e.g. Type EDF Gas Sensor to Baseefa03ATEX0631X or IS Transmitter Type EDS/C(P) to BAS02ATEX1233) which can detect a wide range of flammable and toxic gases depending on the type of sensor used.

There are 2 control units:

- ED810- designed for 12v or 24v DC power supplies
- ED811 designed for mains power supplies.

The control circuits are housed, together with up to 4 Zener barriers Type ZB1 to BAS99ATEX7149U (which provide voltage and current limitations for up to 4 remote gas sensors) and terminals for the electrical connections, in a plastic or metal enclosure which provides a degree of protection of at least IP20.

Supply - Non-hazardous Area Terminals

 $U_{\rm m} = 253 {\rm V}$

Output Parameters (per Channel, 1-4)

$U_{\rm o} = 8.8 \mathrm{V}$	$C_{\rm i} = 0$
$I_{\rm o} = 1.043 {\rm A}$	$L_{i} = 0$
$P_{\rm o} = 2 {\rm W}$	

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the load connection to each channel must not exceed the following values:

Group	Capacitance	Inductance or L/R Ratio		
	μF	mH	μΗ/Ω	
IIC	6.8 (8.8)	30	14	
IIB	24.4 (26.4)	90	42	
IIA	68.4 (70.4)	240	112	

Figures in the parentheses may be used when connected to Gas Sensor Type EDF.

16 Report Number

See Certificate History

17 Specific Conditions of Use

None.

18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product, and conformity is demonstrated in the report:

Clause	Subject	Compliance
1.2.7	Protection against other hazards (LVD type requirements, etc.)	Manufacturer responsibility
1.4.1	External effects	User/Installer responsibility
1.4.2	Aggressive substances, etc.	User/Installer responsibility

BAS-CERT-081



Description

ED810 Front Panel Label ED811 Front Panel Label

19 Drawings and Documents

New drawings submitted for this issue of certificate:

Number	Sheet	Issue	Date
FPDGMV6	1 of 1	-	07/12/2021
FPDGMV4	1 of 1	-	07/12/2021

These drawings are common to BAS21UKEX0600.

Current drawings which remain unaffected by this issue:

Number	Sheet	Issue	Date	Description
FPDGMV4.cdr	1 of 1	-	11	ED810 Front Panel Label
ED10BBCT	1 of 1	5	12.3.08	ED810 Base PCB Circuit Diagram
810 Overlay	1 of 1	2	8.3.08	ED810 PCB Overlay
ED810LO-atex	1 of 2	2	8.3.08	ED810 PCB Artwork
ED810/1 GA	1 of 1	-	2.7.03	ED810 and ED811 General Assembly
Fpdgmv2.cdr	1 of 2	-	24.11.03	ED810 Front Panel Label
Fpdgmv2.cdr	2 of 2	-	24.11.03	ED811 Front Panel Label
ED810BBCL-ATEX	1 of 1	1	29.5.03	ATEX Approved Model
ED811BBCT	1 of 1	4	28.5.03	ED811 Baseboard Circuit Diagram
ED811BBCT-ATEX	1 of 1	2	5.6.03	ATEX Approved Model
811 Overlay	1 of 1	1	28.5.03	ED811BB PCB Revision for ATEX
ED811LO-atex	1 & 2	1	28.5.03	ED811BB PCB Revision for ATEX

All drawings are common to BAS21UKEX0600 and held with Baseefa03ATEX0507.

20 Certificate History

Certificate No.	Date	Comments
Baseefa03ATEX0507	30 November 2004	The release of the prime certificate. The associated test and assessment is documented in Test Report No. 03(C)0528
Baseefa03ATEX0507/1	21 August 2008	To permit minor changes to the enclosure, circuit diagram and layout of the Base PCB. See project 08/0279.
Baseefa03ATEX0507/2	11 June 2013	To permit a logo change. This issue of the certificate incorporates previously issued primary & supplementary certificates into one certificate. See project 13/0496.
Baseefa03ATEX0507 Issue 3	7 December 2021	To confirm that the design conforms to the requirements of EN IEC 60079-0:2018 and EN 60079-11:2012 including a change to the marking in line with the later standards. The associated test and assessment is documented in Test Report No. 20(C)0453/04.
For drawings applicable to each	h issue, see original of	that issue.

Certificate Number BAS21UKEX0600

1



UK-TYPE EXAMINATION CERTIFICATE

2 Equipment or Protective System Intended for use in Potentially Explosive Atmospheres UKSI 2016:1107 (as amended) – Schedule 3A, Part 1

- **3** UK-Type Examination **BAS21UKEX0600** Certificate Number:
- 4 Product: Gas Detector Type ED81*
- 5 Manufacturer: Electronic Devices Ltd
- 6 Address: Malvern, Worcestershire, WR14 1GB
- 7 This product and any acceptable variation thereto is specified in the schedule to this certificate and the documents therein referred to.
- 8 SGS Baseefa, Approved Body number 1180, in accordance with Regulation 43 of the Equipment and Protective Systems Intended for Use in Potentially Explosive Atmospheres Regulations 2016, UKSI 2016:1107 (as amended), certifies that this product has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of products intended for use in potentially explosive atmospheres given in Schedule 1 of the Regulations.

The examination and test results are recorded in confidential Report No. 21(C)0147/02

9 Compliance with the Essential Health and Safety Requirements has been assured by compliance with:

EN 60079-0: 2018 EN 60079-11: 2012

except in respect of those requirements listed at item 18 of the Schedule.

- 10 If the sign "X" is placed after the certificate number, it indicates that the product is subject to the Specific Conditions of Use specified in the schedule to this certificate.
- 11 This UK-TYPE EXAMINATION CERTIFICATE relates only to the design and construction of the specified product. Further requirements of the Regulations apply to the manufacturing process and supply of this product. These are not covered by this certificate.
- 12 The marking of the product shall include the following:

 $\langle E_X \rangle$ II (1)G [Ex ia Ga] IIC (-20°C \leq Ta \leq +60°C)

SGS Baseefa Customer Reference No. 0344

Project File No. 21/0147

This document is issued by the Company subject to its General Conditions for Certification Services accessible at http://www.sgs.com/en/Terms-and-Conditions.aspx. Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained herein reflects the Company's findings at the time of its intervention only and within the limits of Client's instructions, if any. It does not necessarily indicate that the equipment may be used in particular industries or circumstances. The Company's sole responsibility is to its Client and this document does not excent in full, schedule included, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.

SGS Baseefa Limited Rockhead Business Park, Staden Lane, Buxton, Derbyshire SK17 9RZ Telephone +44 (0) 1298 766600 Fax +44 (0) 1298 766601 e-mail baseefa@sgs.com web site www.sgs.co.uk/sgsbaseefa Registered in England No. 4305578. Registered address: Rossmore Business Park, Ellesmere Port, Cheshire, CH65 3EN



R S SINCLAIR TECHNICAL MANAGER On behalf of SGS Baseefa Limited

BAS-CertUK-001 Issue 2 SGS Fimko OY is an associate of SGS Baseefa Limited



Schedule

Certificate Number BAS21UKEX0600

15 Description of Product

A Gas Detector Type ED81* is a control unit designed to power and monitor up to 4 remote gas sensors (e.g. Type EDF Gas Sensor to Baseefa03ATEX0631X or IS Transmitter Type EDS/C(P) to BAS02ATEX1233) which can detect a wide range of flammable and toxic gases depending on the type of sensor used.

There are 2 control units:

- ED810- designed for 12v or 24v DC power supplies
- ED811 designed for mains power supplies.

The control circuits is housed, together with up to 4 zener barriers Type ZB1 to BAS99ATEX7149U (which provide voltage and current limitations for up to 4 remote gas sensors) and terminals for the electrical connections, in a plastic or metal enclosure which provides a degree of protection of at least IP20.

Supply - Non-hazardous Are Terminals

 $U_{\rm m} = 253 \mathrm{V}$

13

14

Output Parameters (per Channel, 1-4)

 $U_{o} = 8.8V$ $C_{i} = 0$ $I_{o} = 1.043A$ $L_{i} = 0$ $P_{o} = 2W$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the load connection to each channel must not exceed the following values:

Group	Capacitance	Inductance or L/R Ratio		
	μF	mH	μΗ/Ω	
IIC	6.8 (8.8)	30	14	
IIB	24.4 (26.4)	90	42	
IIA	68.4 (70.4)	240	112	

Figures in the parentheses may be used when connected to Gas Sensor Type EDF.

16 Report Number

21(C)0147/02

17 Specific Conditions of Use

None

18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product, and conformity is demonstrated in the report:

Clause	Subject	Compliance
1.2.7	LVD type requirements	Manufacturer responsibility
1.4.1	External effects	User/Installer responsibility
1.4.2	Aggressive substances, etc.	User/Installer responsibility

BAS-CertUK-001 Issue 2 SGS Fimko OY is an associate of SGS Baseefa Limited



19 Drawings and Documents

Number	Sheet	Issue	Date	Description		
FPDGMV6	1 of 1	-	07/12/2021	ED810 Front Panel Label		
FPDGMV4	1 of 1	-	07/12/2021	ED811 Front Panel Label		
These drawings are held with BAS21UKEX0600.						

For other current drawings not re-submitted for this assessment, see Baseefa03ATEX0507 Issue 3.



1	EU - TY	PE EXAMINATION CERTIFICATE					
2	Equipment or Protectiv	e System Intended for use in Potentially Explosive Atmospheres Directive 2014/34/EU					
3	EU - Type Examination Certificate Number:	BAS99ATEX7149U – Issue 2					
3.1	In accordance with Article 41 of Directistence prior to the date of applicat with Directive 2014/34/EU. Supple certificates, may continue to bear the	rective 2014/34/EU, EC-Type Examination Certificates referring to 94/9/EC that were in ion of 2014/34/EU (20 April 2016) may be referenced as if they were issued in accordance mentary Certificates to such EC-Type Examination Certificates, and new issues of such original certificate number issued prior to 20 April 2016.					
4	Product:	Shunt Zener Diode Safety Barrier Modules Type ZB*					
5	Manufacturer: Electronic Devices Ltd						
6	Address: Malvern, Worcestershire, WR14 1GB						
7	This re-issued certificate extends EC constructed in accordance with the sp in the Schedule attached to this certificate to the schedule attached	Type Examination Certificate No. BAS99ATEX7149U to apply to product designed and ecification set out in the Schedule of the said certificate but having any variations specified icate and the documents therein referred to.					
8	SGS Fimko Oy, Notified Body number and of the Council, dated 26 Februar Safety Requirements relating to the or given in Annex II to the Directive.	er 0598, in accordance with Article 17 of Directive 2014/34/EU of the European Parliament y 2014, certifies that this product has been found to comply with the Essential Health and lesign and construction of products intended for use in potentially explosive atmospheres					
8.1	The original certificate was issued by The Electrical Equipment Certification Service (UK Notified Body 0600). It, and an supplements previously issued by SGS Baseefa Ltd (UK Notified Body 1180) have been transferred to the supervision of SGS Finko Oy (EU Notified Body 0598). The original certificate number is retained.						
	The examination and test results are r	ecorded in confidential Report No. See Certificate History					
9	Compliance with the Essential Health	and Safety Requirements has been assured by compliance with:					
	EN IEC 60079-0:2018 EN 6	0079-11:2012					
	except in respect of those requiremen	ts listed at item 18 of the Schedule.					
10	If the sign "X" is placed after the ce specified in the schedule to this certif	rtificate number, it indicates that the product is subject to the Specific Conditions of Use icate.					
11	This EU - TYPE EXAMINATION C requirements of the Directive apply certificate.	ERTIFICATE relates only to the design and construction of the specified product. Further to the manufacturing process and supply of this product. These are not covered by this					

12 The marking of the product shall include the following:

See Schedule

SGS Fimko Oy Customer Reference No. 0334

Project File No. 20/0453

This document is issued by the Company subject to their General Conditions for Certification Services accessible at http://www.sgs.com/en/Terms-and-Conditions.aspx. Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained herein reflects the Company's findings at the time of their intervention only and within the limits of Client's instructions, if any. It does not necessarily indicate that the equipment may be used in particular industries or circumstances. The Company's sole responsibility is to its Client and this document does not exonerate parties to a transaction from exercising all their rights and obligations under the transaction documents. This document cannot be reproduced except in full, schedule included, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.

SGS Fimko Oy Takomotie 8

FI-00380 Helsinki, Finland Telephone +358 (0)9 696 361 e-mail <u>sgs.fimko@sgs.com</u> web site <u>www.sgs.fi</u>

Business ID 0978538-5 Member of the SGS Group (SGA SA)

Tucina III

Tuomas Hänninen SGS Fimko Oy

BAS-CERT-086

SGS Baseefa Limited is an associate of SGS Fimko OY

Issue 2



Schedule

13

14

Certificate Number BAS99ATEX7149U - Issue 2

15 Description of Product

Shunt Zener Diode Safety Barriers Types ZB* are designed to restrict the transfer of energy from non-intrinsically safe circuits to intrinsically safe circuits by the limitation of voltage and current.

Each barrier consists of a network of fuses, zener diodes and resistors, all encapsulated in a plastic case and electrical connections made via an asymmetrical arrangement of connector pins (of which 4 are earth) which are designed for PCB mounting. With the exception of the connector pins, the case provides a degree of protection of a least IP20.

The series consist of a total of five double channel barrier modules and one single channel barrier module for Group IIC and one single channel barrier module for Group IIB, details of which are listed in the tables below:

B II (1)G [Ex ia Ga] IIC (-20°C \leq Ta \leq +60°C) ZB1 – ZB6

ⓐ II (1)G [Ex ia Ga] IIB (-20°C ≤ Ta ≤ +60°C) ZB8

Input Parameters

Ch.1+i/p, Ch2. +i/p, Ch1&2 -i/p;

 $U_{\rm m}=253{
m V}$

Output Parameters

Barrier	Description (Nominal)	Terminals	U ₀ (V)	I _a (mA)	P₀(mW)	Factory of Safety
ZB1	8V, 10R	Ch 1 o/p	7.88	830	1580	>5
	8V, 39R	Ch 2 o/p	7.88	213	420	>20
		Ch 1 + Ch2	7.88	1043	2000	4.8
ZB2	8V, 18R	Ch 1 o/p	7.88	460	700	>10
	8V, 18R	Ch 2 o/p	7.88	460	700	>10
		Ch 1 + Ch2	7.88	920	1400	>5
ZB3	20V, 150R	Ch 1 o/p	21V	147	770	2.7
	20V, 150R	Ch 2 o/p	21V	147	770	2.7
		Ch 1 + Ch2		Not Pe	ermitted	1
ZB4	8V, 220R	Ch 1 o/p	7.88V	38	74	>100
	8V, 220R	Ch 2 o/p	7.88V	38	74	>100
		Ch 1 + Ch2	7.88V	76	148	>50
ZB5	8V, 1KR	Ch 1 o/p	7.88V	8.3	16	>100
ZB6	20V, 180R	Ch 1 o/p	21V	123	645	3.2
	20V, 180R	Ch 2 o/p	21V	123	645	3.2
		Ch 1 + Ch2	21V	246	1290	1.6
ZB8	15V, 22R	Ch 1 o/p	15.75	754	2.967	3.5

BAS-CERT-086

Issue 2



The above barriers may be positive of negative polarity but both channels must be of like polarity.

Load Parameters

The capacitance and either the inductance or the inductance to resistance (L/R) ratio of the hazardous area load must not exceed the following values for Group IIC:

Barrier	Terminals	Capacitance	Inductance	or L/R Ratio
		μΓ	mH	μΗ/Ω
	Ch 1	8.8	0.06	17
ZB1	Ch 2	8.8	0.06	17
	Ch 1 + Ch 2	8.8	0.03	14
	Ch 1	8.8	0.18	30
ZB2	Ch 2	8.8	0.18	30
	Ch 1 + Ch 2	8.8	0.04	15
	Ch 1	0.188	1.45	36
ZB3	Ch 2	0.188	1.45	36
	Ch 1 + Ch 2		Not Permitted	
ZB4	Ch 1	8.8	25	350
	Ch 2	8.8	25	350
	Ch 1 + Ch 2	8.8	6.42	181
ZB5	Ch 1	8.8	492	790
ZB6	Ch 1	0.188	2.47	56
	Ch 2	0.188	2.47	56
	Ch 1 + Ch 2	0.188	0.16	29

The values for Groups IIB and IIA are 3 and 8 times the values shown for Group IIC respectively.

The capacitance and either the inductance or the inductance to resistance (L/R) ratio of the hazardous area load must not exceed the following values for Group IIB:

Barrier	Terminals	Capacitance	Inductance or L/R Ratio	
		μF	mH	μΗ/Ω
ZB8	Ch 1	2.9	300	47.8

16 Report Number

See Certificate History

17 Specific Conditions of Use

1. The Shunt Zener Diode Safety Barrier Modules must be mounted with suitable connection facilities such that the external connectors are provided with a degree of protection of at least IP20.

18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product, and conformity is demonstrated in the report: 21(C)0453/01

BAS-CERT-086

Issue 2

Certificate Number BAS99ATEX7149U Issue 2



Clause	Subject	Compliance
1.2.7	Protection against other hazards (LVD type requirements, etc.)	Manufacturer responsibility
1.4.1	External effects	User/Installer responsibility
1.4.2	Aggressive substances, etc.	User/Installer responsibility

19 Drawings and Documents

New drawings submitted for this issue of certificate:

Number	Sheet	Issue	Date	Description		
ZB CL	1 of 1	4	16.08.21	ZB COMPONENT LIST		
ZBL	1 of 1	4	24.08.21	ZB Label diagram		
These drawings are common to BAS21UKEX0599U.						

These drawings are common to DAS2101(DA057)0.

Current drawings which remain unaffected by this issue:

Number	Sheet	Issue	Date	Description	
ZB8 CCT	1 of 1	1	09.03.09	Double Zener Barrier Type ZB8	
ZB8LO	1 of 1	1	06.04.09	ZB8 PCB Layout	
ZBGA	1 of 1	3	09.03.09	Zener Barrier Type ZB	
All drawings are common to BAS2111/EV050011 and held with BAS00ATEV071401					

All drawings are common to BAS21UKEX0599U and held with BAS99ATEX07149U.

20 Certificate History

Certificate No.	Date	Comments	
BAS99ATEX07149U	27 April 2001	The release of the prime certificate. The associated test and assessment is documented in Test Report No. 98(CI)0660.	
BAS99ATEX07149U /1	11 May 2009	To permit the addition of a Type ZB8 Zener Barrier for Group IIB to the range of Safety Barrier Modules. The associated test and assessment is documented in Test Report No. 09(CI)0211	
BAS99ATEX07149U Issue 2	7 December 2021	To confirm that the design conforms to the requirements of EN IEC 60079-0:2018 and EN 60079-11:2012 including a change to the marking in line with the later standards. Additionally, to accept minor electrical changes not affecting the original assessment. The associated test and assessment is documented in Test Report No. 20(C)0453/01.	
For drawings applicable to each issue, see original of that issue.			



UK-TYPE EXAMINATION CERTIFICATE

2 Equipment or Protective System Intended for use in Potentially Explosive Atmospheres UKSI 2016:1107 (as amended) – Schedule 3A, Part 1

- **3** UK-Type Examination **BAS21UKEX0599U** Certificate Number:
- 4 Product: Shunt Zener Diode Safety Barrier Modules Type ZB*
- 5 Manufacturer: Electronic Devices Ltd
- 6 Address: Malvern, Worcestershire, WR14 1GB
- 7 This product and any acceptable variation thereto is specified in the schedule to this certificate and the documents therein referred to.
- 8 SGS Baseefa, Approved Body number 1180, in accordance with Regulation 43 of the Equipment and Protective Systems Intended for Use in Potentially Explosive Atmospheres Regulations 2016, UKSI 2016:1107 (as amended), certifies that this product has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of products intended for use in potentially explosive atmospheres given in Schedule 1 of the Regulations.

The examination and test results are recorded in confidential Report No. 21(C)0147/01

9 Compliance with the Essential Health and Safety Requirements has been assured by compliance with:

EN IEC 60079-0: 2018 EN 60079-11: 2012

except in respect of those requirements listed at item 18 of the Schedule.

- 10 If the sign "X" is placed after the certificate number, it indicates that the product is subject to the Specific Conditions of Use specified in the schedule to this certificate.
- 11 This UK-TYPE EXAMINATION CERTIFICATE relates only to the design and construction of the specified product. Further requirements of the Regulations apply to the manufacturing process and supply of this product. These are not covered by this certificate.
- **12** The marking of the product shall include the following:

See Schedule

SGS Baseefa Customer Reference No. 0344

Project File No. 21/0147

This document is issued by the Company subject to its General Conditions for Certification Services accessible at http://www.sgs.com/en/Terms-and-Conditions.aspx Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained herein reflects the Company's findings at the time of its intervention only and within the limits of Client's instructions, if any. It does not necessarily indicate that the equipment may be used in particular industries or circumstances. The Company's sole responsibility is to its Client and this document does not excent in full, schedule included, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.



Rockhead Business Park, Staden Lane, Buxton, Derbyshire SK17 9RZ Telephone +44 (0) 1298 766600 Fax +44 (0) 1298 766601 e-mail <u>baseefa@sgs.com</u> web site <u>www.sgs.co.uk/sgsbaseefa</u> Registered in England No. 4305578. Registered address: Rossmore Business Park, Ellesmere Port, Cheshire, CH65 3EN



R S SINCLAIR TECHNICAL MANAGER On behalf of SGS Baseefa Limited

BAS-CertUK-001 Issue 2

ED811 IM REV 8 - 11.02.2025

SGS Fimko OY is an associate of SGS Baseefa Limited



Schedule

14

13

Certificate Number BAS21UKEX0559U

15 Description of Product

Shunt Zener Diode Safety Barriers Types ZB* are designed to restrict the transfer of energy from non-intrinsically safe circuits to intrinsically safe circuits by the limitation of voltage and current.

Each barrier consists of a network of fuses, zener diodes and resistors, all encapsulated in a plastic case and electrical connections made via an asymmetrical arrangement of connector pins (of which 4 are earth) which are designed for PCB mounting. With the exception of the connector pins, the case provides a degree of protection of a least IP20.

The series consist of a total of five double channel barrier modules and one single channel barrier module for Group IIC and one single channel barrier module for Group IIB, details of which are listed in the tables below:

B II (1)G [Ex ia Ga] IIC (-20°C \leq Ta \leq +60°C) ZB1 – ZB6

ⓑ II (1)G [Ex ia Ga] IIB (-20°C ≤ Ta ≤ +60°C) ZB8

Input Parameters

Ch.1+i/p, Ch2. +i/p, Ch1&2 -i/p;

 $U_{\rm m}$ =253V

Output Parameters

Barrier	Description (Nominal)	Terminals	U ₀ (V)	I _a (mA)	P ₀ (mW)	Factory of Safety
ZB1	8V, 10R	Ch 1 o/p	7.88	830	1580	>5
	8V, 39R	Ch 2 o/p	7.88	213	420	>20
		Ch 1 + Ch2	7.88	1043	2000	4.8
ZB2	8V, 18R	Ch 1 o/p	7.88	460	700	>10
	8V, 18R	Ch 2 o/p	7.88	460	700	>10
		Ch 1 + Ch2	7.88	920	1400	>5
ZB3	20V, 150R	Ch 1 o/p	21V	147	770	2.7
	20V, 150R	Ch 2 o/p	21V	147	770	2.7
		Ch 1 + Ch2		Not Pe	ermitted	
ZB4	8V, 220R	Ch 1 o/p	7.88V	38	74	>100
	8V, 220R	Ch 2 o/p	7.88V	38	74	>100
		Ch 1 + Ch2	7.88V	76	148	>50
ZB5	8V, 1KR	Ch 1 o/p	7.88V	8.3	16	>100
ZB6	20V, 180R	Ch 1 o/p	21V	123	645	3.2
	20V, 180R	Ch 2 o/p	21V	123	645	3.2
		Ch 1 + Ch2	21V	246	1290	1.6
ZB8	15V, 22R	Ch 1 o/p	15.75	754	2.967	3.5

BAS-CertUK-001 Issue 2 SGS Fimko OY is an associate of SGS Baseefa Limited



The above barriers may be positive of negative polarity but both channels must be of like polarity.

Load Parameters

The capacitance and either the inductance or the inductance to resistance (L/R) ratio of the hazardous area load must not exceed the following values for Group IIC:

Barrier	Terminals	Capacitance	Inductance or L/R Ratio		
		μΓ	mH	$\mu \mathrm{H}/\Omega$	
	Ch 1	8.8	0.06	17	
ZB1	Ch 2	8.8	0.06	17	
	Ch 1 + Ch 2	8.8	0.03	14	
	Ch 1	8.8	0.18	30	
ZB2	Ch 2	8.8	0.18	30	
	Ch 1 + Ch 2	8.8	0.04	15	
	Ch 1	0.188	1.45	36	
ZB3	Ch 2	0.188	1.45	36	
	Ch 1 + Ch 2	Not Permitted			
ZB4	Ch 1	8.8	25	350	
	Ch 2	8.8	25	350	
	Ch 1 + Ch 2	8.8	6.42	181	
ZB5	Ch 1	8.8	492	790	
ZB6	Ch 1	0.188	2.47	56	
	Ch 2	0.188	2.47	56	
	Ch 1 + Ch 2	0.188	0.16	29	

The values for Groups IIB and IIA are 3 and 8 times the values shown for Group IIC respectively.

The capacitance and either the inductance or the inductance to resistance (L/R) ratio of the hazardous area load must not exceed the following values for Group IIB:

Barrier	Terminals	Capacitance	Inductance or L/R Ratio	
		μΓ	mH	μΗ/Ω
ZB8	Ch 1	2.9	300	47.8

16 Report Number

21(C)0147/01

17 Specific Conditions of Use

None

18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product, and conformity is demonstrated in the report:

BAS-CertUK-001 Issue 2 SGS Fimko OY is an associate of SGS Baseefa Limited

Certificate Number BAS21UKEX0599U



Issued 7 December 2021 Page 4 of 4

25

Clause	Subject	Compliance
1.2.7	LVD type requirements	Manufacturer responsibility
1.4.1	External effects	User/Installer responsibility
1.4.2	Aggressive substances, etc.	User/Installer responsibility

19 Drawings and Documents

Number	Sheet	Issue	Date	Description		
ZB CL	1 of 1	4	16.08.21	ZB COMPONENT LIST		
ZBL	1 of 1	4	24.08.21	ZB Label diagram		
These drawings are held with BAS21UKEX0599U.						

For other current drawings not re-submitted for this assessment, see BAS99ATEX7149U - Issue 2

BAS-CertUK-001 Issue 2